

Specifications

Keyboard:

- 61 keys
- Touch control: Soft (light), medium (standard), hard (heavier), fixed

Sound generator:

- Sound generator: Stereo PCM sound generator
- Maximum polyphony: 64 voices

Sounds: 790 sounds, 59 drum kits (including a GM-compatible sound set)

Sound sets: 200

Style performance: 270 styles x 4 set

Effects:

- Keyboard part: 2 stereo digital multi-effects
- Accompaniment part: 2 stereo digital multi-effects
- 173 variations

Styles:

- 270 styles
- Style control: 2 intros, 4 variations, 2 fills, 1 break, 2 endings, synchro start, tap tempo

Audio player

Supported formats: MP3 (44.1 kHz, 16-bit), WAV (44.1 kHz, 16-bit)

Sequencer:

Record:

- Supports real-time recording
- 16 tracks, 999 songs maximum
- Data storage capacity: 100,000 notes (999 songs)

Playback:

- Supports song play (playing the keyboard while playing back a song)

Supported formats:

- Playback: SMF (Standard MIDI File) format 0 or 1
- Recording: Original format (a function is available to convert and output to SMF0)

Demo songs: 3 (songs + sound introduction)

Scales: 11 types (including user scale)

Connectors:

FOOT CONTROLLER jack: 6.3 mm phone jack (half-damper not supported)

AUDIO IN jack: 3.5 mm stereo mini-phone jack

OUTPUT L/MONO, R jacks: 6.3 mm TS phone jack (unbalanced)

Headphones jack: 3.5 mm stereo mini-phone jack

USB TO DEVICE port: USB Type A port (for connecting a USB flash drive)

USB TO HOST port: USB Type B port (for connecting to a computer)

MIDI OUT connector: For connecting to MIDI tone generators and other devices

MIDI: Supports MIDI OUT, USB MIDI

Display: Customizable LCD with backlighting

Power supply:

- Power adapter: AC adapter (DC 12V,)
- Batteries: AA batteries (alkaline or nickel-metal hydride) × 6 (sold separately)
- Battery life: Approx. 8 hr. (when using alkaline batteries)

Power consumption: 6W

Dimensions (W × D × H): 1,037 mm × 296 mm × 80 mm/40.83" × 11.65" × 3.15"

Weight: 4 kg/8.82 lbs. (excluding batteries)

Included items: Quick Start Guide (this document), Precautions, AC adapter